

## Light Fittings for Fluorescent Lamp


### BAY51-Q Series Explosion-proof Light Fittings for Fluorescent Lamp



- ◆ Explosion Protection to
  - CENELEC
  - IEC
  - NEC
- ◆ Can be used in
  - Zone 1 and Zone 2
  - Zone 21 and Zone 22
  - Class I, Zone 1 and Zone 2
  - Class I, Division 2, Groups A, B, C, D
- ◆ Two enclosure types: Type I and Type II
- ◆ Available lamp and power
  - T8 Fluorescent Lamps: 18W x 1, 36W x 1, 18W x 2, 36W x 2
- ◆ Enclosure in glass fiber reinforced polyester(GRP), diffuser in polycarbonate, corrosion-proof.
- ◆ Ex e enclosure with explosion-proof components inside.
- ◆ Safety interlock between enclosure and diffuser, switches off on opening.
- ◆ Built-in electronic ballast, power factor  $\geq 0.95$ .
- ◆ Emergency unit with protections against overcharge and over-discharge.
- ◆ End of lamp life (EOL) rectification effect protection.



#### Catalogue number logic



**Zones 1&2; 21&22**

# Light Fittings for Fluorescent Lamp

## BAY51-Q Series Explosion-proof Light Fittings for Fluorescent Lamp

### Technical data

#### Explosion-proof light fittings for fluorescent lamp BAY51-Q□ × □□

<b>Explosion protection</b>	Ex II 2 G Ex d e q IIC T4 Gb Ex II 2 D Ex t IIIC T80°C Db IP66
<b>Certificates</b>	LCIE 12 ATEX 3045X; IECEx CQM 07.0007 RU C-CN.ГБ05.В.00344 (CU-TR)
<b>Conformity to standards</b>	EN 60079-0, EN 60079-1, EN 60079-5, EN 60079-7, EN 60079-31 IEC 60079-0, IEC 60079-1, IEC 60079-5, IEC 60079-7, IEC 60079-31
<b>Material</b>	GRP, stands 7J impact, corrosion-proof Polycarbonate, 90% light transmission, stands 7J impact Electronic ballast, power factor ≥ 0.95, with protection against short circuit, overload, lamp aging, lamp damage and dissymmetry power of lamp tube. Certificate No.: LCIE 06 ATEX 0003U; IECEx CQM 07.0005U
Exposed fastener	Stainless steel
<b>Interlock</b>	BZX-6 explosion-proof distance switch, switching off on opening Certificate No.: LCIE 06 ATEX 0002U, IECEx CQM 07.0006U
<b>Lamp</b>	T8 tube (supplied with the light fittings)
Lamp specification	36W x 2   18W x 2
Lamp power (W)	36W x 1   18W x 1
<b>Rated voltage</b>	96~254V AC 50/60Hz
<b>Degree of protection</b>	IP66, IP67(optional)
<b>Ambient temperature</b>	-20°C~+55°C
<b>Terminal</b>	3 x 1.5~4mm <sup>2</sup> (L+N+PE)
<b>Cable entries</b>	4 x Φ26: 2 x M25 x 1.5 cable glands (DQM-I Ex e, plastic), 2 x M25 x 1.5 plugs.
<b>Available cable outer diameter</b>	Φ9~Φ16 (mm)



### Selection table

Type / Ordering code	Lamp power(W)	Weight(kg)	Type / Ordering code	Lamp power(W)	Weight(kg)
BAY51-Q18 x 1L	18 x 1	6.80	BAY51-Q18 x 2L	18 x 2	7.00
BAY51-Q18 x 1X	18 x 1	6.70	BAY51-Q18 x 2X	18 x 2	6.90
BAY51-Q18 x 1B	18 x 1	7.80	BAY51-Q18 x 2B	18 x 2	7.90
BAY51-Q18 x 1D	18 x 1	8.10	BAY51-Q18 x 2D	18 x 2	8.20
BAY51-Q18 x 1G	18 x 1	7.70	BAY51-Q18 x 2G	18 x 2	7.85
BAY51-Q36 x 1L	36 x 1	11.40	BAY51-Q36 x 2L	36 x 2	11.60
BAY51-Q36 x 1X	36 x 1	11.30	BAY51-Q36 x 2X	36 x 2	11.40
BAY51-Q36 x 1B	36 x 1	12.30	BAY51-Q36 x 2B	36 x 2	12.50
BAY51-Q36 x 1D	36 x 1	12.60	BAY51-Q36 x 2D	36 x 2	12.75
BAY51-Q36 x 1G	36 x 1	12.20	BAY51-Q36 x 2G	36 x 2	12.40

**Note:** Products above include all the mounting accessories listed in Mounting Accessories & Spare Parts Table (see P2/6~7).

## Light Fittings for Fluorescent Lamp

### BAY51-Q Series Explosion-proof Light Fittings for Fluorescent Lamp

#### Technical data

#### Explosion-proof emergency light fittings for fluorescent lamp BAY51-Q□ × □□J

<b>Explosion protection</b>	<b>Ex II 2 G Ex d e q IIC T4 Gb</b> <b>Ex II 2 D Ex tb IIIC T80°C Db IP66</b>					
<b>Certificates</b>	TÜV CY 18 ATEX 0206027X; IECEx CQM 12.0002X; CU-TR					
<b>Conformity to standards</b>	EN 60079-0, EN 60079-1, EN 60079-5, EN 60079-7, EN 60079-31 IEC 60079-0, IEC 60079-1, IEC 60079-5, IEC 60079-7, IEC 60079-31					
<b>Material</b>	Enclosure: GRP, stands 7J impact, corrosion-proof Diffuser: Polycarbonate, 90% light transmission, stands 7J impact Ballast: Electronic ballast, power factor ≥ 0.95, with protection against short circuit, overload, lamp aging, lamp damage and dissymmetry power of lamp tube. Emergency controller: BY-2 emergency controller Exposed fastener: Certificate No.: LCIE 10 ATEX 3010U, IECEx CQM 11.0041U Stainless steel					
<b>Lamp</b>	Lamp specification: T8 tube (supplied with the light fittings) <table border="1" style="margin-left: auto; margin-right: auto;"> <tr> <td>36W x 2</td> <td>18W x 2</td> </tr> <tr> <td>36W x 1</td> <td>18W x 1</td> </tr> </table>		36W x 2	18W x 2	36W x 1	18W x 1
36W x 2	18W x 2					
36W x 1	18W x 1					
<b>Emergency power (W)</b>	36W x 1, 18W x 1					
<b>Emergency starting time</b>	0.3s					
<b>Charging time</b>	24h					
<b>Emergency lighting time</b>	120min (180min is optional)					
<b>Rated voltage</b>	96~254V AC 50/60Hz					
<b>Degree of protection</b>	IP66, IP67(optional)					
<b>Ambient temperature</b>	-20°C~+55°C					
<b>Terminal</b>	3 x 1.5~4mm <sup>2</sup> (L+N+PE)					
<b>Cable entries</b>	4 x Φ26: 2 x M25 x 1.5 cable glands (DQM-I Ex e, plastic), 2 x M25 x 1.5 plugs.					
<b>Available cable outer diameter</b>	Φ9~Φ16 (mm)					

#### Selection table

Type / Ordering code	Lamp power(W)	Weight(kg)	Type / Ordering code	Lamp power(W)	Weight(kg)
BAY51-Q18 x 1LJ	18 x 1	8.65	BAY51-Q18 x 2LJ	18 x 2	8.80
BAY51-Q18 x 1XJ	18 x 1	8.50	BAY51-Q18 x 2XJ	18 x 2	8.70
BAY51-Q18 x 1BJ	18 x 1	9.60	BAY51-Q18 x 2BJ	18 x 2	9.75
BAY51-Q18 x 1DJ	18 x 1	9.90	BAY51-Q18 x 2DJ	18 x 2	10.00
BAY51-Q18 x 1GJ	18 x 1	9.50	BAY51-Q18 x 2GJ	18 x 2	9.65
BAY51-Q36 x 1LJ	36 x 1	13.00	BAY51-Q36 x 2LJ	36 x 2	13.05
BAY51-Q36 x 1XJ	36 x 1	12.95	BAY51-Q36 x 2XJ	36 x 2	13.10
BAY51-Q36 x 1BJ	36 x 1	14.00	BAY51-Q36 x 2BJ	36 x 2	14.10
BAY51-Q36 x 1DJ	36 x 1	14.30	BAY51-Q36 x 2DJ	36 x 2	14.45
BAY51-Q36 x 1GJ	36 x 1	13.90	BAY51-Q36 x 2GJ	36 x 2	14.05

**Note:** Products above include all the mounting accessories listed in Mounting Accessories & Spare Parts Table (see P2/6~7).




# Light Fittings for Fluorescent Lamp

## BAY51-Q Series Explosion-proof Light Fittings for Fluorescent Lamp

### Photometric data


BAY51-Q18x1□□

Rated luminous flux  
18Wx1: 1300lm




BAY51-Q18x2□□

Rated luminous flux  
18Wx2: 2600lm




BAY51-Q36x1□□

Rated luminous flux  
36Wx1: 3250lm




BAY51-Q36x2□□

Rated luminous flux  
36Wx2: 6500lm




We can provide lighting design and data by professional lighting software DIALUX based upon simulated site situation on request.

### Dimension drawings (all dimensions in mm) - subject to alteration



BAY51-Q18 x □ □ □



BAY51-Q36 x □ □ □


## Light Fittings for Fluorescent Lamp

### BAY51-Q Series Explosion-proof Light Fittings for Fluorescent Lamp


#### Mounting type (all dimensions in mm) – subject to alteration

##### Installation reference


D: pendant chain type




G: pendant pole type




L: pole type (the pole is provided by user)



Suitable for ground pole type




Suitable for fence pole type




Suitable for wall pole type

X: ceiling type



B: wall type



#### Mounting Accessories & Spare Parts Table

Supplied according to the mounting type

Mounting type	Accessories				Ordering code	Weight (kg)
	Name	Qty	Illustration			
D: pendant chain type	①.Sucker	2			5136017	0.15
	②.Chain	2	Length: 450mm		5136016	0.08
	⑤.Mounting bracket	2	Stainless steel, same as pendant pole type		5136030	0.07
G: pendant pole type	③.Mounting bracket	2			51S01G1	0.04
	④.M8 Screw	2	Stainless steel, length: 350mm		51S01G2	0.12
	⑤.Mounting bracket	2			5136030	0.07




Note: Accessories not in the table shall be supplied by user.

# Light Fittings for Fluorescent Lamp

## BAY51-Q Series Explosion-proof Light Fittings for Fluorescent Lamp


### Mounting Accessories & Spare Parts Table

Supplied according to the mounting type

Mounting type	Accessories			Ordering code	Weight (kg)	
	Name	Qty	Illustration			
L: pole type	⑥.Mounting bracket	2		5136012	0.04	
	⑦.G1 1/2" Pipe clamp	2		5136014	0.04	
	⑤.Mounting bracket	2	Stainless steel, same as pendant pole type		5136030	0.07
X: ceiling type	⑧.Mounting bracket	2		5136015	0.20	
B: wall type	⑨.Wall bracket	2	Stainless steel, welded sheet steel		5136B02	0.62

Note: Accessories not in the table shall be supplied by user.

### Schematic diagram (BAY51-Q□x□□J, T8 fluorescent lamp)



Note: Tube for lamp 2 shall be default for single tube fittings.

### Accessories

Picture	Name	Ordering code	Weight (kg)
	Explosion-proof distance switch	5136003	0.04
	Spanner	5136004	0.02
	Lamp holder (with wires)	5136005	0.02
	YK36DF-2CS electronic ballast (T8/36W)	5136011	1.30
	YK18DF-2CS electronic ballast (T8/18W)	5118004	1.30
	BY-2 emergency controller (with battery) (T8/36W)	5136019	1.70
	BY-2 emergency controller (with battery) (T8/18W)	5118005	1.70